

MaxLi⁺®

Battery Charger
Intelligent / Smart **12/24V 4/8/15A**



P-TECH15A12V24V

BATTERY CHARGE + **MAINTAINER**



SAFETY PROTECTION

- ✓ Reverse polarity
- ✓ Overheat
- ✓ Short circuit
- ✓ Low voltage
- ✓ Overcharge




6-STEP SMART CHARGER

- ✓ Heavy duty applications
- ✓ Cars
- ✓ Boats
- ✓ Equipment



MAINTAIN

- ✓ Safely leave connected to battery indefinitely
- ✓ Extended battery life
- ✓ Optimal performance with zero overcharge



Microprocessor
Controlled



Incl. Trickle
Charging Mode



Led Indication



Multiple Charging
Characteristics



230V~50Hz



TECHNICAL DATA

INPUT	230V, 50Hz
OUTPUT	270W
CHARGER TYPE	6-Step Smart Charger
TYPE OF BATTERIES	12V DC/24V DC Lead-acid batteries (WET, MF, Ca/Ca, AGM and GEL)
CHARGING CURRENT	12V: 4/15 AMPS, 24V: 4/8 AMPS
BATTERY CAPACITY	3 - 300Ah
INSULATION CLASS	IP65
LCD INDICATION	Green = Charging; Blue = Full
CABLE LENGTH	1,5 m
WARRANTY	2 years

6-STEP CHARGING

1
2
3
4
5
6

- Status Check:** After the selection of the charging mode the charger checks the status of the battery (voltage detection).
- Rescue Function:** Saves the battery with impulse charging.
- Bulk:** Charging with maximum charging current and adjusted voltage.
- Absorption:** Charging with steady charging voltage until the capacity has reached 100% again.
- Charging Performance Check:** Charging complete with temporary surveillance of the charging performance.
- Maintenance Charge:** Battery capacity will be kept at 95-100% and the battery volatge will be supervised. If necessary the charger will give an impulse to the battery to keep it completely recharged.



Auto | Marine | RV | Powersport | Lawn & Garden